

PATENT

Please amend the claims as follows:

1. (Previously Presented) A method for adjusting transmit power levels of a plurality of transmissions in a wireless communication system, the method comprising:
receiving a first indication of a received quality of a first transmission;
adjusting the transmit power level of the first transmission based at least in part on the first indication;
receiving a second indication of a received quality of a second transmission, wherein the second indication is formed by aggregating a plurality of power control bits allocated for feedback for the second transmission, wherein the aggregating lowers the rate of the plurality of power control bits; and
adjusting the transmit power level of the second transmission based at least in part on the second indication.
2. (Original) The method of claim 1, wherein the first indication comprises a power control command that indicates whether to increase or decrease the transmit power level of the first transmission.
3. (Original) The method of claim 2, wherein the transmit power levels of the first and second transmissions are adjusted together based on the power control command.
4. (Original) The method of claim 3, wherein a difference between the transmit power levels of the first and second transmissions is adjusted based on the second indication.
5. (Original) The method of claim 2, wherein the power control command is generated based on a comparison of the received quality of the first transmission against a setpoint.

PATENT

6. (Original) The method of claim 1, wherein the transmit power levels for the first and second transmissions are adjusted based solely on the first and second indications, respectively.

7. (Original) The method of claim 1, wherein second indication comprises an erasure indicator bit indicating whether a frame in the second transmission was received correctly or in error.

8. (Original) The method of claim 1, wherein second indication comprises a quality indicator bit indicating the quality of a received frame in the second transmission.

9. (Currently Amended) The method of claim 1, further comprising:
receiving a third indication of a received quality of a third transmission, wherein the third indication is formed by aggregating a plurality of bits allocated for feedback for the ~~second~~ third transmission; and
adjusting the transmit power level of the third transmission based at least in part on the third indication.

10. (Original) The method of claim 1, wherein the first indication is received via a first power control sub-channel and the second indication is received via a second power control sub-channel.

11. (Original) The method of claim 10, wherein the first and second power control sub-channels are formed by time division multiplexing a power control channel.

12. (Original) The method of claim 10, wherein a combined bit rate of the first and second power control sub-channels is limited to a particular bit rate.

PATENT

13. (Original) The method of claim 10, wherein bits allocated for the second power control sub-channel are aggregated to form the feedback for the second transmission at a lower rate but having increased reliability.

14. (Original) The method of claim 13, wherein the feedback rate of the second transmission is based at least in part on a frame size of the second transmission.

15. (Original) The method of claim 13, wherein the feedback rate of the second transmission is selectable from among a set of possible feedback rates.

16. (Original) The method of claim 10, wherein the second power control sub-channel is operative to send a plurality of metrics for the second transmission.

17. (Original) The method of claim 16, wherein one of the plurality of metrics indicates a step size for adjustment of the transmit power level for the second transmission.

18. (Original) The method of claim 16, wherein one of the plurality of metrics is indicative of an amount of margin in the received quality of the second transmission for no frame erasure.

19. (Original) The method of claim 1, wherein the wireless communication system is a CDMA system that conforms to cdma2000 standard or W-CDMA standard, or both.

20. (Previously Presented) A method for adjusting transmit power levels of a plurality of transmissions in a wireless communication system, the method comprising:

receiving and processing a first transmission to determine a received quality of the first transmission;

forming a first indication for the received quality of the first transmission;

receiving and processing a second transmission to determine a received quality of the second transmission;

PATENT

forming a second indication for the received quality of the second transmission; and
sending the first and second indications via first and second power control sub-channels,
respectively, and

wherein the second indication is form by aggregating a plurality of power control bits
allocated for feedback for the second transmission, wherein the aggregating lowers the rate of the
plurality of power control bits.

21. (Original) The method of claim 20, further comprising:
determining a duration of an interruption in the receiving and processing of the first
transmission; and
signaling for an increase in the transmit power level for the first transmission if the
duration of the interruption is less than a particular time period.

22. (Previously Presented) The method of claim 21, wherein the signaling is
performed if the duration of the interruption is less than or equal to half a period of a frame in the
first transmission.

23. (Previously Presented) The method of claim 21, wherein an amount of increase in
the transmit power level for the first transmission is based on the duration of the interruption and
the period of a frame in the first transmission.

24. (Previously Presented) A power control unit for use in a wireless communication
system, comprising:
a signal quality measurement unit operative to receive and process a first transmission to
provide a first indication for a first metric for the first transmission;
a data processor operative to receive and process a second transmission to provide a
second indication for a second metric for the second transmission;
a power control processor coupled to the signal quality measurement unit and the data
processor, the power control processor operative to direct transmission of the first and second
indications on first and second power control sub-channels, respectively, and

PATENT

wherein the second indication is formed by aggregating a plurality of power control bits allocated for feedback for the second transmission, wherein the aggregating lowers the rate of the plurality of power control bits.

25. (Cancelled)

26. (Previously Presented) A power control unit within a base station in a wireless communication system, comprising:

a channel processor operative to receive and process a received signal to recover a first indication of a received quality of a first transmission and a second indication of a received quality of a second transmission, wherein the second indication is formed by aggregating a plurality of power control bits allocated for feedback for the second transmission, wherein the aggregating lowers the rate of the plurality of power control bits; and

a power control processor coupled to the channel processor and operative to receive the first and second indications and provide one or more commands to adjust transmit power levels of the first and second transmissions.

27. (Previously Presented) The method of claim 5, wherein the setpoint is adjusted based on the received quality of the first transmission.

28. (Previously Presented) The method of claim 5, wherein the setpoint is adjusted upward responsive to the received quality of the first transmission being greater than the setpoint.

29. (Previously Presented) The method of claim 5, wherein the setpoint is adjusted downward responsive to the received quality of the first transmission being less than the setpoint.

30. (Previously Presented) The method of claim 28, wherein the setpoint is adjusted downward responsive to the received quality of the first transmission being less than the setpoint.

31. (Previously Presented) The method of claim 5, wherein a period between adjustments in setpoint is adjustable.

PATENT

32. (Previously Presented) The method of claim 28, wherein a period between successive upward adjustments in the setpoint is adjustable.

33. (Previously Presented) The method of claim 29, wherein a period between successive downward adjustments in setpoint is adjustable.

34. (Previously Presented) The method of claim 30, wherein the amount of upward adjustment in setpoint is independent of the amount of downward adjustment in setpoint.

35. (Previously Presented) A method for adjusting transmit power levels of a plurality of transmissions in a wireless communication system, the method comprising:
receiving a first indication of a received quality of a first transmission;
adjusting the transmit power level of the first transmission based at least in part on the first indication;
receiving a second indication of a received quality of a second transmission, wherein the second indication is formed by aggregating a plurality of power control bits allocated for feedback for the second transmission, wherein the plurality of power control bits have a rate equal to that of the first indication, and wherein the aggregating lowers the rate of the plurality of power control bits; and
adjusting the transmit power level of the second transmission based at least in part on the second indication.